

Description

The Arduino Modugno® Vibro, powered by an on-board STM32C011F4 microcontroller, features a compact vibration motor (VZ43FM1B8230001L) for haptic feedback and alert applications. This setup enables simple vibration control via I2C and provides tactile notifications for various interactive projects.

Target Areas

Maker, beginner, education



Contents

1 Application Examples	3
2 Features	4
2.1 Contents	4
3 Related Products	4
4 Rating	4
4.1 Recommended Operating Conditions	4
5 Power Tree	5
6 Block Diagram	5
7 Functional Overview	6
7.1 Technical Specifications (Module-Specific)	6
7.2 Pinout	7
7.3 Power Specifications	9
7.4 Mechanical Information	9
7.5 I2C Address Reference	10
7.5.1 Pull-up Resistors	12
8 Device Operation	12
8.1 Getting Started	12
9 Certifications Summary	13
10 Declaration of Conformity CE DoC (EU)	13
11 Declaration of Conformity to EU RoHS & REACH 211 01/19/2021	
12 FCC WARNING	14
13 IC Caution	14
14 Conflict Minerals Declaration	14



1 Application Examples

- **Haptic Feedback** Provide tactile notifications in wearable devices, gaming controllers, or interactive interfaces to enhance user experience.
- **Alert Systems** Create vibration-based alerts for notifications, alarms, or status indicators in IoT projects where audio alerts might not be suitable.
- **Interactive Art** Integrate tactile feedback into art installations, musical instruments, or sensory experiences to create engaging multi-modal interactions.



2 Features

- **Compact vibration motor** (VZ43FM1B8230001L) providing strong tactile feedback at 12,000 rpm.
- Integrated **STM32C011F4** microcontroller providing I2C interface by default.
- **N-channel MOSFET** (2N7002KT1G) for efficient motor control..
- Designed for **3.3V** operation via the Qwiic connector (I2C).
- Ideal for **haptic feedback** and **vibration alerts** in interactive projects.

2.1 Contents

SKU	Name	Purpose	Quantity
ABX00130	Modulino® Vibro	Vibration motor for haptic feedback	1
	I2C Qwiic cable	Compatible with the Qwiic standard	1

3 Related Products

- *SKU: ASX00027* - Arduino® Sensor Kit
- *SKU: K000007* - Arduino® Starter Kit
- *SKU: AKX00026* - Arduino® Oplà IoT Kit
- *SKU: AKX00069* - Arduino® Plug and Make Kit

4 Rating

4.1 Recommended Operating Conditions


- **Powered at 3.3 V** through the Qwiic interface (in accordance with the Qwiic standard)
- **Operating temperature:** -40 °C to +85 °C

Typical current consumption:

- Microcontroller: ~3.4 mA
- Motor active: ~67 mA typical, 85 mA maximum

5 Power Tree


The power tree for the Modulino® Vibro can be consulted below:



Modulino® Vibro Power Tree

6 Block Diagram

This node includes an STM32C011F4 microcontroller that controls a vibration motor through an N-channel MOSFET. It communicates via I2C by default, but can be reprogrammed via SWD for custom functionality.



Modulino® Vibro Block Diagram

7 Functional Overview

The Modulino® Vibro node receives vibration commands via I2C and controls the VZ43FM1B8230001L motor through a 2N7002KT1G N-channel MOSFET. The STM32C011F4 microcontroller manages PWM control for variable intensity vibration patterns. Advanced users can re-flash the microcontroller via SWD for custom vibration sequences or additional logic.

7.1 Technical Specifications (Module-Specific)

Specification	Details
Microcontroller	STM32C011F4
Motor	VZ43FM1B8230001L vibration motor
Motor Speed	12,000 rpm rated
Supply Voltage	3.3 V
Power Consumption	~3.4 mA (MCU) + 67 mA typical (motor active)
Motor Current	67 mA typical, 85 mA maximum
Communication	I2C (Qwiic), SWD (reprogramming), UART (option)

7.2 Pinout

Qwiic / I2C (1×4 Header)


Pin	Function
GND	Ground
3.3 V	Power Supply (3.3 V)
SDA	I2C Data
SCL	I2C Clock

These pads and the Qwiic connectors share the same I2C bus at 3.3 V.

Additional 1×8 Header (Motor & MCU Signals)

Pin	Function
GND	Ground
3V3	3.3 V Power
PF2	RESET (NRST)
SWCLK	SWD Clock (PA14)
SWDIO	SWD Data (PA13)
TX1	USART Transmit (PA9)
RX1	USART Receive (PA10)
PA2	Motor Control (MOSFET gate)

Note: PA0 controls the N-channel MOSFET gate to switch the vibration motor on/off. You can also access additional microcontroller pins (PA1, PA2, PA3, PA5) via test pads for custom applications.



Legend:	Digital	I2C	Other SERIAL
	Power	SPI	Analog
	Ground	UART/USART	PWM/Timer
	Main Part		


Modulino Vibro
SKU code: ABX00130
Pinout
Last update: 12 Sep, 2025

Pinout Overview

7.3 Power Specifications


- **Nominal operating voltage:** 3.3 V via Qwiic

7.4 Mechanical Information



Modulino® Vibro Mechanical Information

- Board dimensions: 41 mm × 25.36 mm
- Thickness: 1.6 mm (±0.2 mm)
- Four mounting holes (∅ 3.2 mm)
 - Hole spacing: 16 mm vertically, 32 mm horizontally
- **Breadboard compatible:** 1×4 header and 1×8 header spaced by 900 mil (22.86 mm)




Blank silk for identification

7.5.1 Pull-up Resistors

This module has pads for optional I2C pull-up mounting in both data lines. No resistors are mounted by default but in case the resistors are needed 4.7 K resistors in an SMD 0402 format are recommended.

These are positioned near the Qwiic connector on the power LED side. These are positioned near the Qwiic connector on the power LED side.



Generic pull-up resistor position

8 Device Operation

By default, the board is an I2C target device. It manages motor control through integrated firmware via PWM signals to the MOSFET gate. Simply connect it to a 3.3 V Qwiic interface and send I2C commands for various vibration patterns. If needed, you can reprogram the STM32C011F4 via SWD to modify or extend functionality.

8.1 Getting Started

Use any standard Arduino workflow-desktop IDE or Arduino Cloud Editor. The official Modulino library provides simple commands for vibration control including intensity and duration settings. Ensure your power supply can handle the additional 67-85 mA current when the motor is active.

Certifications

9 Certifications Summary

Certification	Status
CE/RED (Europe)	Yes
UKCA (UK)	Yes
FCC (USA)	Yes
IC (Canada)	Yes
RoHS	Yes
REACH	Yes
WEEE	Yes

10 Declaration of Conformity CE DoC (EU)

We declare under our sole responsibility that the products above are in conformity with the essential requirements of the following EU Directives and therefore qualify for free movement within markets comprising the European Union (EU) and European Economic Area (EEA).

11 Declaration of Conformity to EU RoHS & REACH 211

01/19/2021

Arduino boards are in compliance with RoHS 2 Directive 2011/65/EU of the European Parliament and RoHS 3 Directive 2015/863/EU of the Council of 4 June 2015 on the restriction of the use of certain hazardous substances in electrical and electronic equipment.

Substance	Maximum limit (ppm)
Lead (Pb)	1000
Cadmium (Cd)	100
Mercury (Hg)	1000
Hexavalent Chromium (Cr6+)	1000
Poly Brominated Biphenyls (PBB)	1000
Poly Brominated Diphenyl ethers (PBDE)	1000
Bis(2-Ethylhexyl) phthalate (DEHP)	1000
Benzyl butyl phthalate (BBP)	1000
Dibutyl phthalate (DBP)	1000
Diisobutyl phthalate (DIBP)	1000

Exemptions: No exemptions are claimed.

Arduino Boards are fully compliant with the related requirements of European Union Regulation (EC) 1907 /2006 concerning the Registration, Evaluation, Authorization and Restriction of Chemicals (REACH). We declare none of the SVHCs (<https://echa.europa.eu/web/guest/candidate-list-table>), the Candidate List of Substances of Very High



Concern for authorization currently released by ECHA, is present in all products (and also package) in quantities totaling in a concentration equal or above 0.1%. To the best of our knowledge, we also declare that our products do not contain any of the substances listed on the "Authorization List" (Annex XIV of the REACH regulations) and Substances of Very High Concern (SVHC) in any significant amounts as specified by the Annex XVII of Candidate list published by ECHA (European Chemical Agency) 1907 /2006/EC.

12 FCC WARNING

This device complies with part 15 of the FCC Rules.

Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

13 IC Caution

This device complies with Industry Canada licence-exempt RSS standard(s).

Operation is subject to the following two conditions:

(1) This device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

14 Conflict Minerals Declaration

As a global supplier of electronic and electrical components, Arduino is aware of our obligations with regard to laws and regulations regarding Conflict Minerals, specifically the Dodd-Frank Wall Street Reform and Consumer Protection Act, Section 1502. Arduino does not directly source or process conflict minerals such as Tin, Tantalum, Tungsten, or Gold. Conflict minerals are contained in our products in the form of solder or as a component in metal alloys. As part of our reasonable due diligence, Arduino has contacted component suppliers within our supply chain to verify their continued compliance with the regulations. Based on the information received thus far we declare that our products contain Conflict Minerals sourced from conflict-free areas.



Company Information

Company name	Arduino SRL
Company Address	Via Andrea Appiani, 25 - 20900 MONZA (Italy)

Reference Documentation

Ref	Link
Arduino IDE (Desktop)	https://www.arduino.cc/en/software/
Arduino Courses	https://www.arduino.cc/education/courses
Arduino Documentation	https://docs.arduino.cc/
Arduino IDE (Cloud)	https://create.arduino.cc/editor
Cloud IDE Getting Started	https://docs.arduino.cc/cloud/web-editor/tutorials/getting-started/getting-started-web-editor
Project Hub	https://projecthub.arduino.cc/
Library Reference	https://github.com/arduino-libraries/
Online Store	https://store.arduino.cc/

Revision History

Date	Revision	Changes
14/10/2025	1	First release